

**OCF “Ipanema” – Writing "oxmsel" and "owned"– Security WG CR 3047**

Legal Disclaimer

THIS IS A DRAFT SPECIFICATION DOCUMENT ONLY AND HAS NOT BEEN ADOPTED BY THE OPEN CONNECTIVITY FOUNDATION. THIS DRAFT DOCUMENT MAY NOT BE RELIED UPON FOR ANY PURPOSE OTHER THAN REVIEW OF THE CURRENT STATE OF THE DEVELOPMENT OF THIS DRAFT DOCUMENT. THE OPEN CONNECTIVITY FOUNDATION AND ITS MEMBERS RESERVE THE RIGHT WITHOUT NOTICE TO YOU TO CHANGE ANY OR ALL PORTIONS HEREOF, DELETE PORTIONS HEREOF, MAKE ADDITIONS HERETO, DISCARD THIS DRAFT DOCUMENT IN ITS ENTIRETY OR OTHERWISE MODIFY THIS DRAFT DOCUMENT AT ANY TIME. YOU SHOULD NOT AND MAY NOT RELY UPON THIS DRAFT DOCUMENT IN ANY WAY, INCLUDING BUT NOT LIMITED TO THE DEVELOPMENT OF ANY PRODUCTS OR SERVICES. IMPLEMENTATION OF THIS DRAFT DOCUMENT IS DONE AT YOUR OWN RISK AMEND AND IT IS NOT SUBJECT TO ANY LICENSING GRANTS OR COMMITMENTS UNDER THE OPEN CONNECTIVITY FOUNDATION INTELLECTUAL PROPERTY RIGHTS POLICY OR OTHERWISE. IN CONSIDERATION OF THE OPEN CONNECTIVITY FOUNDATION GRANTING YOU ACCESS TO THIS DRAFT DOCUMENT, YOU DO HEREBY WAIVE ANY AND ALL CLAIMS ASSOCIATED HEREWITH INCLUDING BUT NOT LIMITED TO THOSE CLAIMS DISCUSSED BELOW, AS WELL AS CLAIMS OF DETRIMENTAL RELIANCE.

The OCF logo is a trademark of Open Connectivity Foundation, Inc. in the United States or other countries. \*Other names and brands may be claimed as the property of others.

Copyright © 2020 Open Connectivity Foundation, Inc. All rights reserved.

Copying or other form of reproduction and/or distribution of these works are strictly prohibited.

DRAFT

**\*\*\*\*\* Changes to Table 25 in section 13.2.1 \*\*\*\*\***

**Table 1 – Properties of the "/>**

Property Title	Property Name	Value Type	Value Rule	Mandatory	Device State	Access Mode	Description
OTM	oxms	oic.sec.doxmtype	array	Yes		R	Value identifying the owner-transfer-method and the organization that defined the method.
OTM Selection	oxmsel	oic.sec.doxmtype	UINT16	Yes	RESET	R	Server shall set to (4) "oic.sec.oxm.self"
					RFOTM (no open DOC)	RW	DOTS shall set to its selected DOTS and both parties execute the DOTS. After secure owner transfer session is established DOTS shall update the oxmsel again making it permanent. If the DOTS fails the Server shall transition device state to RESET.
					RFOTM (open DOC)	R	n/a
					RFPRO	R	n/a
					RFNOP	R	n/a
					SRESET	R	n/a
Supported Credential Types	sct	oic.sec.credtype	bitmask	Yes		R	Identifies the types of credentials the Device supports. The Server sets this value at framework initialization after determining security capabilities.
Device Ownership Status	owned	Boolean	T F	Yes	RESET	R	Server shall set to FALSE.
					RFOTM (no open DOC)	R	FALSE
					RFOTM (open DOC)	RW	DOTS (Device communicating over DOC) shall set to TRUE after secure owner transfer session is established.
					RFPRO	R	TRUE
					RFNOP	R	TRUE.
					SRESET	R	TRUE.
Device UUID	deviceuuid	String	oic.sec.didtype	Yes	RESET	R	Server shall construct a temporary random UUID that differs for each transition to RESET.
					RFOTM (no open DOC)	R	n/a
					RFOTM (open DOC)	RW	DOTS (Device communicating over DOC) shall update to a value it has selected after secure owner transfer session is established. If update fails with error PROPERTY_NOT_FOUND the DOTS shall either accept the Server provided value or update

							/doxm.owned=FALSE and terminate the session.
					RFPRO	R	n/a
					RFNOP	R	n/a
					SRESET	R	n/a
Device Owner Id	devowneruuid	String	uuid	Yes	RESET	R	Server shall set to the nil uuid value (e.g. "00000000-0000-0000-0000-000000000000" )
					RFOTM (no open DOC)	R	n/a
					RFOTM (open DOC)	RW	DOTS (Device communicating over DOC) shall set value after secure owner transfer session is established.
					RFPRO	R	n/a
					RFNOP	R	n/a
					SRESET	R	n/a
Resource Owner Id	rowneruuid	String	uuid	Yes	RESET	R	Server shall set to the nil uuid value (e.g. "00000000-0000-0000-0000-000000000000" )
					RFOTM (no open DOC)	R	n/a
					RFOTM (open DOC)	RW	The DOTS (Device communicating over DOC) shall configure the rowneruuid Property when a successful owner transfer session is established.
					RFPRO	R	n/a
					RFNOP	R	n/a
					SRESET	RW	The DOTS (referenced via "devowneruuid" Property) should verify and if needed, update the resource owner Property when a mutually authenticated secure session is established. If the "rowneruuid" does not refer to a valid DOTS device identifier the Server shall transition to RESET Device state.

\*\*\*\*\* End of Change \*\*\*\*\*